

XRA400

REF. 2155



- Application in analogue RA microrepeaters for 2, 3 or 4 UHF channels.
- It combines the single-channel signals coming from LRA+HRA pairs while reducing emission of noise and intermodulation products.
- Frontal made of galvanized steel with plastic covering.
- Rack format 19".

XRA-40

Frequency band	MHz	470-862
No. of input channels *		up to 4
Minimum channel spacing		2 channels
Insertion loss	dB	1.3 to 2.2
Isolation between inputs	dB	≥ 13
Ripple	dB	< ± 0.6
Input/output impedance	Ω	75
Output return loss	dB	> 14
Outside dimensions		19"x1Ux240mm
RF connectors		F female
Max. dimensions		19" x 1U x 240mm

* Specify number of channels when ordering.